

## Welcome to Vernier LabQuest Emulator 1.1

---

The LabQuest Emulator (LQM) is computer software that can be used to demonstrate the functions of a LabQuest on a computer. Usually this is done in order to project the image for a group presentation. The emulator performs almost all functions of the LabQuest itself, including collecting data from a LabQuest unit connected to the computer.

This version of LQM contains LabQuest App version 1.1, released in April 2008. It is available for Windows XP and Vista only.

## Collect Data with LabQuest Emulator

---

Here's how to quickly collect some data with LQM.

1. Wake up your LabQuest by pressing the silver power button on the upper left corner.
2. Connect a sensor (auto-ID capable) to one of the ports on your LabQuest.
3. Launch LQM. After a short startup delay, LQM will find the LabQuest, and then detect the sensor.
4. At this point click on the LQM screen, using the computer mouse, in the same way you would tap the actual LabQuest screen using the stylus. Consult the LabQuest Reference Guide for details on the use of LabQuest App.

## Tools

---

1. Choose Copy Screen from the Edit menu to place a copy of the current LabQuest screen on your computer clipboard. This is useful for creating documentation.
2. Sample data files are provided with LQM. Choose Open from the File menu in LabQuest App, and then open the folder titled **sample\_data**.
3. LQM can open data files from a real LabQuest if they are placed in a special folder before LQM is launched.
  - a. Save a LabQuest file to a USB drive or SD card using Save from the file menu in LabQuest App.
  - b. Copy this file to your computer, and place in the folder **LQM\_user\_files**, located in c:/Program Files/Vernier Software/ LabQuest Emulator/. (Non-default installations may have a different location. A shortcut to this folder is placed in your Start menu under Vernier Software by the LQM installer.
  - c. Launch LQM.
  - d. Choose Open from the File menu in LabQuest App, and navigate to the **LQM\_user\_files** folder. Select your file, and click Open.
4. Since the LQM cannot communicate with a spectrometer or the LabQuest internal microphone, we have provided virtual versions of these sensors for demonstration purposes. Only one virtual sensor can be used at a time.
  - a. Choose Spectrometer from the Virtual Sensor menu to connect a virtual spectrometer for demonstration. You can only collect simulated data, but general operations can be shown.

## LabQuest Emulator

---

- b. Choose Internal Microphone from the Virtual Sensor menu to connect a virtual microphone for demonstration. You can only collect simulated data, but general operations can be shown.
5. LQM can be used without a LabQuest, although you cannot collect data without the hardware. If LQM does not detect a LabQuest at startup time, a dialog will alert you to this. You can choose to continue into LQM without a LabQuest if desired. You can then open files and manipulate data therein.

## Troubleshooting

---

1. Turn on your LabQuest before connecting to your computer, and before launching LQM. LQM will not detect a LabQuest connected after LQM launches.
2. LQM cannot collect data if it is not communicating with a LabQuest. The LQM window title bar will read **LabQuest Connected** once a LabQuest is found, and **No Device Detected** otherwise. An indicator is also displayed in the lower right corner of the LQM screen. It shows a LabQuest with a caution symbol if no LabQuest is detected.
3. If LQM cannot find the LabQuest, check to see if another application such as *Logger Pro* or *Logger Lite* has control of LabQuest. Only one computer application at a time can communicate with a LabQuest. Exit LQM, verify that LabQuest is connected, has power, and is turned on, and then restart LQM.
4. LQM requires at least LabQuest App version 1.1 installed on the LabQuest hardware. Update your LabQuest if it contains version 1.0.

## Limitations

---

1. LQM cannot print.
2. LQM cannot communicate with USB spectrometers.
3. The LabQuest internal microphone is not supported.
4. Any files saved by LQM will be available within the emulator, but you cannot transfer these files to the actual LabQuest, *Logger Pro*, or any other application.

## License Information

---

This product contains certain open source software originated by third parties that is subject to the GNU General Public License as published by the Free Software Foundation, GNU Library/Lesser General Public License (LGPL) and different and/or additional copyright licenses, disclaimers or notices. These licenses give you the right to redistribute and/or modify the software.

The software is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the GNU General Public License for more details.

Complete source code for the open source software is available on request from Vernier Software & Technology. Contact us at [info@vernier.com](mailto:info@vernier.com), or by writing to

## LabQuest Emulator

---

Source Code Request  
Vernier Software & Technology  
13979 SW Millikan Way  
Beaverton OR 97005  
USA

Source code will be made available for download, or you may request a CD-ROM of the code. A shipping and handling fee will be charged for a CD-ROM.

The exact terms of GPL, LGPL and some other licenses are provided to you with the source code distribution. You may also read the license at <http://www.gnu.org/licenses/>

**Vernier Software & Technology**  
13979 S.W. Millikan Way Beaverton, OR 97005-2886  
Toll Free (888) 837-6437 (503) 277-2299 FAX (503) 277-2440  
[info@vernier.com](mailto:info@vernier.com) [www.vernier.com](http://www.vernier.com)

Revised 5/12/08

Logger *Pro*, Logger Lite, Vernier LabQuest, Vernier LabPro, Go! Link, Vernier EasyLink and other marks shown are our trademarks or registered trademarks in the United States.

All other marks not owned by us that appear herein are the property of their respective owners, who may or may not be affiliated with, connected to, or sponsored by us.